

## Level 1 Combiner Box

PV Combiner Box Level 1 to bundle the output lines of individual strings and to connect them to the inverter or optionally to a Level 2 Combiner Box. Smart design customized for each customer's application. Advanced surge-protection devices, fuse links and switch disconnectors keep the correct operation and protection of the system. Additionally, PV Combiner Box fulfills the standard IEC/EN 61439-2 to offer a high reliability on the units supplied.



(Example of Combiner Box. Picture may differ from product)

- 10 string input
- fuse holders in string input (+/-) including fuse links
- surge protection device for DC system voltage
- string input with cable glands
- direct wall mount + plastic wall mount lugs

**PV 210S0F0V000TXPX10KO**

Order reference 8000036546 Rev 2

## Technical Data

### APPLICATION DATA

Operating ambient temperature range	-25 °C to +50 °C
Intended installation location	protected outdoors ( $\leq 1$ km from sea)
Degree of protection (acc. to IEC 60529)	IP65
Conformity with norms	IEC 61439-2 ed 2.0 / EN 61439-2:2011

### ELECTRICAL CHARACTERISTICS

Rated DC voltage (Un)	1000 VDC
Rated DC current per input (Inc)	9.4 A at 50 °C ambient
Rated DC current per input (10h short-circuit at main output)	1.25 · Inc
Switch disconnector breaking & making capacity (acc. to IEC 60947-3)	400 A (DC21B 1000 V)
Circuit breaker breaking & making capacity (acc. to IEC 60947-2)	N/A
Contactors breaking & making capacity (acc. to IEC 60947-4-1)	N/A
Switch-disconnector / Circuit breaker / Contactor handle location	direct handle (inside enclosure)
DC earthing system	floating positive and negative
Surge protection on DC ports	1000V DC, type II, I <sub>max</sub> = 40 kA, U <sub>p</sub> $\leq$ 4.0/4.0 kV, aux. contact

### ENCLOSURE

Enclosure dimensions (H x W x D)	647 x 436 x 250 mm
Form factor	cabinet with hinged door(s)
Material	glass-fiber reinforced polyester (GFRP)
Fixing system	direct wall mount + plastic wall mount lugs

## INPUTS

Number of DC inputs (+ & – being one input)	10
Positive DC input wires' to be connected to / cross-section (stranded)	screw connection / 0.75 - 25 mm <sup>2</sup>
Negative DC input wires' to be connected to / cross-section (stranded)	screw connection / 0.75 - 25 mm <sup>2</sup>
Positive / Negative DC input wires' outer diameter	5 - 10 mm
Fuses	fuse-links and fuse-disconnectors
Fuse form factor	10 x 38 mm
Location of fuses	positive and negative inputs
Fuse-link rated current (In)	15 A
Fuse-link time-current characteristic	gPV (EN 60269-6)
Earth wire to be connected to / cross-section (stranded)	screw connection / 2.5 - 35 mm <sup>2</sup>
Earth wire outer diameter	6 - 12 mm

## OUTPUTS

Number of DC outputs (+ & – being one output)	1
DC output wires' to be connected to / cross-section (stranded)	M8 bolt and nut connection / ≤ 185 mm <sup>2</sup>
DC output wires' outer diameter	18 - 25 mm

## OTHERS

Notes	Waterproof combiner box acc. IP65
	Relativity Humidity: up to 95% non-condensating
	Fuse holders with led